

WR 6040 WIRELESS SERIAL RECEIVER

The WR 6040 wireless serial receiver is the gateway that uses reliable frequency-hopping, spread-spectrum technology to decode radio frequency (RF) transmissions from wireless devices and high-power repeaters. It then outputs the decoded data to the central computer. It is connected to a USB port on the central computer and appears as a COM port in the software. The unit comes with an RS-232 serial DB-9 connector and a plug-in transformer ready to install. An RS-232 to USB converter is required.



Specifications:

Dimensions: 6.38"x3.60"x1.10" (162.0 mm x 91.4 mm x 27.9 mm)

Weight: 4.7 oz. (133 g)

Power Requirement: 12vdc at 1 watt

Operating Frequency: 902-928 MHz (USA), 915-925 MHz (AUS), 921-928 MHz (NZ)

Operating Environment: 32 - 140 °F (0 - 60 °C)